

SYSMAC-SE2

Sysmac Studio

Sysmac Studio for machine creators

The Sysmac Studio provides one design and operation environment for configuration, programming, simulation and monitoring.

- One software for motion, logic sequencing, safety, vision and HMI
- Fully compliant with open standard IEC 61131-3
- Supports Ladder, Structured text and In-Line ST programming with a rich instruction set
- CAM editor for easy programming of complex motion profiles
- One simulation tool for sequence and motion in a 3D environment
- Advanced security function with 32 digit security password



System requirements

Item	Requirement
Operating system (OS) ^{*1 *2}	Windows XP (Service Pack 3 or higher, 32-bit version) / Windows Vista (32-bit version) / Windows 7 (32-bit/64 bit version) / Windows 8 (32-bit/64-bit version) / Windows 8.1 (32-bit/64-bit version)
CPU	Windows computers with Celeron 540 (1.8 GHz) or faster CPU Core i5 M520 (2.4 GHz) or equivalent or faster recommended
Main memory ^{*3}	2 GB min. (4 GB min. recommended)
Recommended video memory / video card for using 3D motion trace	Video memory: 512 MB min. Video card: Either of the following video cards: <ul style="list-style-type: none"> • NVIDIA® GeForce® 200 series or higher • ATI RadeonHD5000 series or higher
Hard disk	At least 1.6 GB of available space
Display	XGA 1024 x 768, 16 million colors WXGA 1280 x 800 min. recommended
Disk drive	DVD-ROM drive
Communication ports	USB port corresponded to USB 2.0 or Ethernet port ^{*4}
Supported languages ^{*5}	Japanese, English, German, French, Italian, Spanish, simplified Chinese, traditional Chinese, Korean

^{*1} Sysmac Studio operating system precaution: System requirements and hard disk space may vary with the system environment.

^{*2} The following restrictions apply when Sysmac Studio is used with Microsoft Windows Vista, Windows 7, Windows 8 or Windows 8.1.

1) Some Help files cannot be accessed.

The Help files can be accessed if the Help program distributed by Microsoft for Windows (WinHlp32.exe) is installed. Refer to the Microsoft homepage listed below or contact Microsoft for details on installing the file. (The download page is automatically displayed if the Help files are opened while the user is connected to the Internet.)
<http://support.microsoft.com/kb/917607/en-us>

2) The following restrictions apply to some application operations:

Application	Restriction
CX-Designer	If a new Windows Vista, Windows 7, Windows 8 or Windows 8.1 font (e.g., Meiryo) is used in a project, the font size on labels may be bigger and protrude from the components if the project is transferred from CX-Designer running on a Windows XP or earlier OS to the NS/NSJ.
CX-Integrator/Network Configurator	Although you can install CPS files, EDS files, Expansion Modules and Interface Modules, the virtual store function of Windows Vista, Windows 7, Windows 8 or Windows 8.1 imposes the following restrictions on the use of the software after installation. <ul style="list-style-type: none"> • If another user logs in, the applications data will need to be installed again. • The CPS files will not be automatically updated. These restrictions will not exist if application data is installed using Run as Administrator.

^{*3} The amount of memory required varies with the Support Software used in Sysmac Studio for the following Support Software. Refer to user documentation for individual Support Software for details. CX-Designer, CX-Protocol and Network Configurator.

^{*4} Refer to the hardware manual for your CPU unit for hardware connection methods and cables to connect the computer and CPU unit.

^{*5} Supported only by the Sysmac Studio version 1.01 or higher about German, French, Italian and Spanish. Supported only by the Sysmac Studio version 1.02 or higher about simplified Chinese, traditional Chinese and Korean.

Function specifications

Common specifications

Item		Function	Sysmac Studio	
Setting parameters	EtherCAT configuration and setup	–	You can create a configuration in the Sysmac Studio of the EtherCAT slaves connected to the built-in EtherCAT port of the NJ-series CPU unit and set the parameters for the EtherCAT masters and slaves.	All versions
		Registering slaves	You can set up devices by dragging slaves from the device list displayed in the Toolbox pane to the locations where you want to connect them.	
		Changing the coupler model	You change the model number or unit version of the coupler units. Use this function to change the model number and version of the coupler unit registered in the project to the new model number and version when replacing a coupler unit.	Ver. 1.09 or higher
		Setting master parameters	You set the common parameters of the EtherCAT network (e.g., the fail-soft operation and wait time for slave startup settings.)	All versions
		Setting slave parameters	You set the standard slave parameters and assign PDOs (process data objects).	
		Comparing and merging network configuration information	The EtherCAT network configuration information in the NJ-series CPU unit and in the Sysmac Studio are compared and the differences are displayed.	
		Transferring the network configuration information	The EtherCAT network configuration information is transferred to the NJ-series CPU unit. Or, the EtherCAT network configuration information in the NJ-series CPU unit is transferred to the Sysmac Studio and displayed in the EtherCAT editor.	
		Installing ESI files	ESI (EtherCAT slave information) files are installed.	
	EtherCAT slave terminal configuration and setup	–	The configuration of any slave terminal that is connected to an EtherCAT network is created on the Sysmac Studio. The NX units that compose the slave terminal are set in the configuration.	Ver. 1.06 or higher
		Registering NX units	A slave terminal is built by dragging NX units from the device list displayed in the Toolbox to the locations where you want to mount them.	
		Setting NX units	The I/O allocations, mounting settings and unit operation settings of the NX units are edited.	
		Displaying the width of a slave terminal configuration	The width and power consumption of a slave terminal are displayed based on the unit configuration information.	
		Comparing and merging the slave terminal configuration information	When online, you can compare the configuration information in the project with the physical configuration. You can also select the missing units and add them to the project.	
		Transferring the slave terminal configuration information	The unit configuration information is transferred to the CPU unit.	
	CPU/Expansion rack configuration and setup	–	You create the configuration in the Sysmac Studio of the Units mounted in the NJ-series CPU rack and Expansion racks and the special units.	All versions
		Registering units	A rack is built by dragging units from the device list displayed in the Toolbox Pane to the locations where you want to mount them.	
		Creating racks	An Expansion rack (power supply unit, I/O interface unit and end cover) is added.	
		Switching unit displays	The model number, unit number and slot number are displayed.	
		Setting special units	The input time constants are set for input units and parameters are set for special units.	
		Displaying rack widths, current consumption and power consumption	The rack widths, current consumption and power consumption are displayed based on the unit configuration information.	
		Comparing the CPU/Expansion rack configuration information with the physical configuration	When online, you can compare the configuration information in the project with the physical configuration. You can also select the missing units and add them.	
		Transferring the CPU/Expansion rack configuration information	The unit configuration information is transferred to the CPU unit. The synchronize function is used.	
	Controller setup	–	The controller setup is used to change settings related to the operation of the controller. The controller setup contains PLC function module operation settings and built-in EtherNet/IP function module port settings.	
		Operation settings	The startup mode, SD memory card diagnosis at startup, write protection at startup, controller error level changes ¹ and other settings are made.	
		Transferring operation settings	Use the synchronize operation to transfer the operation settings to the NJ-series CPU unit.	
		Built-in EtherNet/IP port settings	These settings are made to perform communications using the built-in EtherNet/IP port of the NJ-series CPU unit.	
	Motion control setup	–	The motion control setup is used to create the axes to use in motion control instructions, assign those axes to servo drives and encoders and set axis parameters.	
		Axis settings	Axes are added to the project.	
		Axis setting table	The axis setting table is a table of all registered axis parameters. You can edit any axis parameters here just as you can on the axis settings tab page.	
	Axes group settings	–	You can setup axes to perform interpolated motions as an axes group.	
		Operation settings	Set the axes group number, whether to use the axes group, the composition and the composition axes.	
			Set the interpolated velocity, the maximum interpolated acceleration and deceleration, and the interpolated operation settings.	

Item		Function	Sysmac Studio		
Setting parameters	Cam data settings	-	The cam data settings are used to create electronic cam data. When you build the project for the controller, a cam table is created according to the cam data settings.	All versions	
		Registering cam data	Cam data settings are added to the project.		
		Editing cam data	You can set properties and node points for cam data settings.		
		Transferring cam data	You can select to transfer all or part of the cam data.		
		Importing cam data settings	You can import cam data settings from a CSV file.		
		Exporting cam data settings	You can export cam data to a CSV file.		
		Registering cam definitions	You add new cam definitions to change cam table in the program.	Ver 1.09 or higher	
		Editing cam definitions	You set cam definitions.		
		Transferring cam definitions	You transfer cam definitions to the controller.	All versions	
		Exporting cam tables	You can export cam table to a CSV file.		
		Transferring cam tables from the controller to files	You can save a cam table in the NJ-series CPU unit to a CSV file.		
		Transferring cam tables from files to the controller	You can transfer a cam table that is saved in a CSV file to update the contents of a cam table that is already in the NJ-series CPU unit.		
	Superimposing cam table	You can superimpose the cam table from a CSV file on the cam profile curve position graph that is currently displayed.			
	Task setup	-	Programs are executed in tasks in an NJ-series CPU unit. The task settings define the execution period, the execution timing, the programs executed by the task, the I/O refreshing performed by the task and which variables to share between tasks.		
		Registering tasks	The tasks, which are used to execute programs, are registered.		
		Setting task I/O	The task I/O settings define what units the task should perform I/O refreshing for.		
		Assigning programs	Program assignments define what programs a task will execute.		
		Setting exclusive control of variables in tasks	You can specify if a task can write to its own values (known as a refreshing task) or if it can only access them (an accessing task) for global variables. This ensures concurrency for global variable values from all tasks that reference them.		
	I/O map settings	-	The I/O ports that correspond to the registered EtherCAT slaves and to the registered units on the CPU rack and Expansion racks are displayed. The I/O map is edited to assign variables to I/O ports. The variables are used in the user program.		
		Displaying I/O ports	I/O ports are displayed based on the configuration information of the devices (slaves and units).		
		Assigning variables	Variables are assigned to I/O ports.		
		Creating device variables	Device variables are created in the I/O map. You can either automatically create a device variable or manually enter the device variable to create.		
		Checking I/O assignments	The assignments of external I/O devices and variables are checked.		
	Vision sensor settings		You can set and calibrate vision sensors. Refer to "Vision sensor functions" section for more details.	Ver. 1.01 or higher	
	Displacement sensor settings		You can set and calibrate displacement sensors. Refer to "Displacement sensor functions" section for more details.	Ver. 1.05 or higher	
	DB connection function settings		You can set and transfer the DB connection function settings. Refer to "DB connection functions" section for more details.	Ver 1.06 or higher with NJ501-1□20	
EtherNet/IP connection settings		You can make settings related to tag data links (connections) in an EtherNet/IP network. Refer to "EtherNet/IP connection functions" section for more details.	Ver. 1.10 or higher		
EtherNet/IP slave terminal settings		You can make and transfer settings for EtherNet/IP slave terminals. Refer to "EtherNet/IP slave terminal functions" section for more details.	Ver. 1.11 or higher		
NA-series programmable terminal (PT) settings		You can make settings and transfer projects for NA-series programmable terminals. Refer to "HMI functions" section for more details.	Ver. 1.11 or higher		
Programming	Instruction list (Toolbox)		All versions		
	Programming ladder diagrams	-		Ladder diagram programming involves connecting rung components with connecting lines to build algorithms. Rung components and connecting lines are entered in the ladder editor.	
		Starting the ladder editor		The ladder editor for the program is started.	
		Adding and deleting sections		You can divide your ladder diagrams into smaller units for easier management. These units of division are called sections.	
		Inserting rung components		You insert rung components in the ladder editor to create an algorithm.	
		Inserting and deleting function blocks		You can insert a function block instruction or user-defined function block into the ladder editor.	
		Inserting and deleting functions		You can insert a function instruction or user-defined function into the ladder editor.	
		Inserting and deleting inline ST		You can insert a rung component in a ladder diagram to enable programming in ST. This allows you to include ST in a ladder diagram.	
		Editing rung components		You can copy and paste rung components.	
		Inserting and deleting jump labels and jumps		You can insert a jump label in the rung to jump and then specify that jump label when you insert a jump.	
		Inserting and deleting bookmarks		You can add bookmarks to the beginning of rungs and move between them.	
		Rung comments		You can add comments to rungs.	
		Displaying rung errors		When you enter a rung component, the format is always checked and any mistakes are displayed as errors. If there are any errors, a red line is displayed between the rung number and the left bus bar.	
		Entry assistance		When you enter instructions or parameters, each character that you enter from the keyboard narrows the list of candidates that is displayed for selection.	
		Displaying variable comments ^{*2}		A specified variable comment can be displayed with each variable of rung components on the ladder diagrams. You can change the length of the displayed variable comments to make them easier to read. ^{*3}	Ver. 1.01 or higher

Item		Function	Sysmac Studio	
Programming	Programming structured text	–	All versions	
		Starting the ST editor	The ST editor for programs or for functions/function blocks is started.	
		Editing ST	You combine different ST statements to build algorithms.	
		Entering calls to functions and function blocks	You can enter the first character of the instance name of the function or the function block in the ST Editor to call and enter a function or function block.	
		Entering constants	You can enter constants in the ST editor.	
		Entering comments	Enter “(“ at the beginning and “)” at the end of any text to be treated as a comment in the ST editor. If you only want to comment out a single line, enter a double forward slash (//) at the beginning of the line.	
		Copying, pasting and deleting ST elements	You can copy, paste and delete text strings.	
		Indenting	You can indent nested statements to make them easier to read.	
		Moving to a specified line	You can specify a line number to jump directly to that line.	
		Bookmarks	You can add bookmarks to any lines and move between them.	
	Entry assistance	When you enter instructions of parameters, each character that you enter from the keyboard narrows the list of candidates that is displayed for selection.		
	Variable manager	A list of the variables in the global and local variable tables is displayed in a separate window. You can display variable usage, sort and filter the variables, edit and delete variables, or more variables while displaying another editing view.	Ver. 1.04 or higher	
	Changing variable comments and data type comments	You can globally change variable comments and data type comments to other comments. You can change the comments to different language for users in a different country.		
	Sorting and filtering variables	You can sort and filter the variables in each variable table.	Ver 1.08 or higher	
	Searching and replacing	You can search for and replace strings in the data of a project.	All versions	
	Retrace searching	You can search for the program inputs and the input parameters to functions or function blocks that use the selected variable if the selected variable is used as a program output or as the output parameter of a function or function block. Also, you can search for the program outputs and the output parameters to functions or function blocks that use the selected variable if the selected variable is used as a program input or as the input parameter of a function or function block.	Ver. 1.01 or higher	
	Jumping	You can jump to the specified rung number or line number in the program.	All versions	
	Building	–	The programs in the project are converted into a format that is executable in the NJ-series CPU unit.	
		Rebuilding	A rebuild is used to build project programs that have already been built.	
		Aborting a build operation	You can abort a build operation.	
Creating applications for NA-series PT	You can create and transfer pages and subroutines for NA-series programmable terminals. Refer to “HMI functions” section for more details.	Ver. 1.11 or higher		
Reuse functions	Library	–	You can create functions, function block definitions, programs ⁴ and data types in a library file to use them as objects in other projects.	Ver. 1.02 or higher
		Creating libraries	You can create library files to enable using functions, function block definitions and data types in other projects.	
		Using libraries	You can access and reuse objects from library files that were created in other projects.	
File operations	File options	Creating, opening, saving or renaming a project file	You can create, open, save or save under a different name a project file.	All versions
		Project update history management	You can assign numbers to projects to manage the project history.	Ver. 1.03 or higher
		Exporting a project file	You can export a project to an .smc2 or .csm2 project file ⁵ . You can also export a project to a previous project file format, i.e., .smc or .csm ⁶ .	All versions
		Importing a project file	You can import a project from an .smc2 ⁵ , .csm2 ⁵ , .smc or .csm ⁶ project file.	
		Importing a ST project file	Import of ST program files created by the Simulink [®] PLC Coder [™] (version R2013a or higher) from MathWorks [®] Inc.	Ver. 1.04 or higher
		Offline comparison	Compares the data for an open project with the data for a project file and displays the results. You can also compare the open project with an exported .smc2 or .smc project file. Or, you can merge detailed comparison results ⁷ .	Ver. 1.02 or higher
		Cutting, copying and pasting	You can cut, copy or paste items that are selected in the Multiview Explorer or any of the editors.	All versions
	Synchronize	The project file in the computer is compared with the data in the online NJ-series CPU unit and any differences are displayed. You can specify the transfer direction for any type of data and transfer all of the data.		
	Batch transfer	You transfer data between the computer and NJ-series CPU unit that are connected online. You can select the same data to transfer as in the synchronization operation. Unlike the synchronization, the data is transferred in the specified direction without displaying the comparison results.	Ver 1.09 or higher	
	Printing	You can print various data. You can select the items to print.	All versions	
	Clear all memory	The clear all memory menu command is used to initialize the user program, controller configurations and setup, and variables in the CPU unit to the defaults from the Sysmac Studio.		
	SD memory cards	–	The following procedures are used to execute file operations for the SD memory card mounted in the NJ-series CPU unit and to copy files between the SD memory card and computer.	
		Formatting the SD memory card	The SD memory card is formatted.	
		Displaying properties	The properties of the selected file or folder in the SD memory card is displayed.	
Copying files and folders in the SD memory card		The selected file or folder in the SD memory card is copied to the SD memory card.		
Copying files and folders between the SD memory card and the PC		The selected file or folder in the SD memory card is copied to the computer. Or, the selected file or folder in the computer is copied to the SD memory card.		

Item	Function	Sysmac Studio		
Debugging	Monitoring	Variables are monitored during ladder program execution. You can monitor the TRUE/FALSE status of inputs and outputs and the present values of variables in the NJ-series CPU unit. You can monitor operation on the ladder editor, ST editor, watch tab page or I/O map.	All versions	
	Differential monitoring	You can detect the number of times the specified BOOL variable or BOOL member changes to TRUE or FALSE and display the count in the differential monitor window. You can check if bits turn ON and OFF and the number of times that they turn ON and OFF.	Ver. 1.04 or higher	
	Changing present values and TRUE/FALSE	You can change the values of variables that are used in the user program and settings to any desired value and you can change program inputs and outputs to TRUE or FALSE. This allows you to check the operation of the user program and settings.	All versions	
	Changing the present values of variables⁸	You can change the present values of user-defined variables, system-defined variables and device variables as required. You can do this in the ladder editor, ST editor, watch tab page or I/O map.		
	Forced refreshing	Forced refreshing allows the user to refresh external inputs and outputs with user-specified values from the Sysmac Studio. The specified value is retained even if the value of the variable is overwritten from the user program. You can use forced refreshing to force BOOL variables to TRUE or FALSE in the ladder editor, watch tab page or I/O map.		
	Online editing	Online editing allows you to edit programs on systems that are currently in operation. Online editing can be used to edit only POU's and global variables. User-defined data types cannot be edited with online editing.		
	Cross reference tab page	Cross references allow you to see the programs and locations where program elements (variables, data types, I/O ports, functions or function blocks) are used. You can view all locations where an element is used from this list.		
	Data tracing	—	Data tracing allows you to sample the specified variables and store the values of the variables in trace memory without any programming. You can choose between two continuous trace methods: a triggered trace, where you set a trigger condition and data is saved before and after that condition is met, or a continuous trace, in which continuous sampling is performed without any trigger and the results are stored in a file on your computer. However, you can still display data retrieved on the Sysmac Studio and save those results to a file even if you use a triggered trace. These same functions can be used with the simulator as well.	
		Setting sampling intervals	The interval to perform sampling on the target data is set. Sampling is performed for the specified task period, at the specified time, or when a trace sampling instruction is executed.	
		Setting triggers	To perform a triggered trace, you set a condition to trigger sampling. A suitable trigger condition is set to record data before and after an event.	
		Setting a continuous trace	The method to save the data traced during a continuous trace is set.	
		Setting variables to sample	The variables to store in trace memory are registered. The sampling intervals can also be set.	
		Starting and stopping tracing	The data trace settings are transferred to the NJ-series CPU unit and the tracing starts. If you selected <i>Trigger (Single)</i> as the trace type, tracing waits for the trigger to begin sampling. If you selected Continuous, sampling begins immediately and all traced data is transferred to the computer as it is gathered and saved to a file.	
		Displaying trace results	You view the results of the traced data in either a chart or the 3D Motion Monitor. After sampling begins, sample data is immediately transferred and drawn on the graph. The trace target variable table shows the maximum, minimum and average values for each variable. You can change the line colors on the graph. ⁹ You can consecutively read and display continuous trace results from more than one file. ¹⁰	
		Exporting/importing trace results	Trace results are saved within your project automatically when you save the project on the Sysmac Studio. If you want to save this data as a separate file, you can export the data to a CSV file. You can import trace results that you have exported.	
	Printing trace results	You can print out data trace settings along with digital and analog charts.		
	Debugging vision sensors	You can debug the vision sensor offline. Refer to "Vision sensor functions" section for more details.	Ver. 1.01 or higher	
	Debugging displacement sensors	You can debug displacement sensors offline. Refer to "Displacement sensor functions" section for more details.	Ver. 1.05 or higher	
	Simulation	Programs for debugging	You can create programs for debugging that are used only to execute simulations and specify virtual inputs for simulation.	All versions
Executing a simulation		Selecting what to simulate	You can select the programs to simulate from all of the programs in the Sysmac Studio. Programs can be dragged to select them.	
		Setting breakpoints	You can set breakpoints to stop the simulation in the program editor.	
		Executing and stopping simulations	You can control simulation execution to monitor the user program or to check operation through data tracing. Step execution and pausing are also possible.	
			You can perform a linked simulation between sequence control and continuous control (operations controlled by Simulink) to debug the sequence control program and continuous control program ¹¹ .	Ver 1.09 or higher
		Changing the simulation speed	You can change the execution speed.	All versions
		Task period simulation	You can display the task periods.	
		Batch transfer of the present values of variables	You can save the values of variables at specific times during simulations in a file, or you can write the values of variables that were saved in a file back to the simulator. This allows you to write the initial values of variables, e.g., for test applications, before you start a simulation.	Ver. 1.02 or higher
Integrated NS-series PT simulation¹²		You can simulate the linked operation of a sequence program and an NS-series programmable terminal to debug the sequence program and screen data offline.		
Simultaneous simulation of controller and NA-series PT		You can simultaneously simulate sequence control and NA-series PT operation, including displaying pages and subroutines created with Visual Basic and debugging the sequence programming.	Ver. 1.11 or higher	
Setting the virtual equipment	Creating 3D device models	You can create a 3D device model at the control target to monitor with the 3D motion monitor function.	All versions	
	3D motion monitor display mode	You set the axis variables for each element of the 3D equipment model, and then set the 3D equipment into motion according to those axis motions.		
	Displaying 2D paths	You can display the 2D paths of the markers for the projections in the 3D display.		
Monitoring information	Displaying unit production information	You can display the production information of the NJ-series CPU unit and special units, including the models of the units and unit versions.		
	Monitoring task execution times	You can monitor the execution time of each task when the user program is executed on a NJ-series CPU unit or in the simulator. When you are connected to the simulator, you can also monitor the real processing time of tasks. This allows you to perform a controller performance test.		

Item		Function	Sysmac Studio	
Monitoring information	Troubleshooting	–	You can use troubleshooting to check the errors that occurred in the controller, display corrections for the errors and clear the errors.	All versions
		Controller errors	Any current controller errors are displayed. (Observations and information are not displayed.)	
		User-defined errors	Information is displayed on current errors.	
		Controller event log	You can display a log of controller events (including controller errors and controller information). (You cannot display logs from EtherCAT slaves.)	
		User-defined event log	The log of user-defined events that were stored for the create user-defined error (SetAlarm) instruction and the create user-defined information (SetInfo) instruction is displayed.	
		Event settings table	The event setting table is used to register the contents displayed on the Sysmac Studio on HMIs for user-defined events that occur for execution of the create user-defined error (SetAlarm) instruction and the create user-defined information (SetInfo) instruction.	
	User memory usage monitor	An estimate of the space that is used by the user program that you are editing in the Sysmac Studio is displayed in relation to the size of the controller's memory.		
	Setting clock information	You can read and set the NJ-series CPU unit's clock. The computer's clock information is also displayed.		
	DB connection function	You can monitor information for the DB connection. Refer to "DB connection functions" section for more details.	Ver 1.06 or higher with NJ501-1□20	
Communications	Going online with a controller	An online connection is established with the controller. You also can transfer a project from the connected controller to the computer with a simple operation without creating a new project or opening an existing project. ⁵	All versions	
	Checking for forced refreshing	When you go offline, any forced refreshing is cleared.		
Maintenance	Changing the operating mode of the controller	There are two operating modes for NJ-series controllers, depending on if control programs are executed or not. These are RUN mode and PROGRAM mode.	Ver. 1.04 or higher	
	Resetting the controller	The operations and status when the power supply to the controller is cycled are emulated. This can be performed only in PROGRAM mode. You cannot reset the controller in RUN mode.		
	Backup functions	–		You can back up, restore and compare the user program and other NJ-series controller data to replace hardware, such as the CPU unit, or to restore device data.
		Variables and memory backup		You can back up the contents of retained memory to a file and restore the contents of the backup file. You can individually select the retained variables to restore. ¹³
		Controller backup		You can backup data (user program and settings, variable values, memory values, unit settings and slave settings) from a controller to a file and restore the backed up data from the file to the controller.
		SD memory card backup		You can backup the data in the NJ-series CPU unit to an SD memory card mounted in the controller or compare the data in the NJ-series controller to data in the SD memory card.
Importing/exporting to/from backup files	You can import the data in a backup file created for a controller backup or SD memory card backup to a project. Also, you can export project data to a backup file.			
Security measures	Prevention of incorrect connections	Confirming NJ-series CPU unit names and serial IDs	If the name or the serial ID is different between the project and the NJ-series CPU unit when an online connection is established, a confirmation dialog box is displayed.	All versions
		Operation authority verification	You can set five operation authorities (administrator, planning engineer, maintainer, operator and observer) to restrict the operations that can be performed according to the operation authority of the user.	
	Prevention of incorrect operation	Write protection of the CPU unit	You can prevent rewriting of data in the CPU unit from the Sysmac Studio.	
		Prevention of the theft of assets	Authentication of user program execution IDs	
	User program transfer with no restoration information	The program source code is not transferred. If this option is selected, programs are not displayed even if uploaded from another computer. However, variables and settings are transferred even if this option is selected.		
	Password protection for project files	You can place a password on the file to protect your assets.		
	Data protection	You can set passwords for individual POU's (programs, functions and function block definitions) to prohibit displaying, changing and copying them.		
Window operation	Docking	You can dock and undock configuration tab pages, program editors, watch tab pages, cross reference tab page and other window parts to/from the main Sysmac Studio window.	Ver 1.09 or higher	
Online help	Sysmac Studio help system	You can access Sysmac Studio operating procedures.	All versions	
	Instructions reference	Information is provided on how to use the instructions that are supported by the NJ-series CPU units.		
	System-defined variable reference	You can display a list of descriptions of the system-defined variables that you can use on the Sysmac Studio.		
	Keyboard mapping reference	You can display a list of convenient shortcut keys that you can use on the Sysmac Studio.		

¹ Changing event levels for controller errors is supported by version 1.04 or higher.

² Displaying comments for members of arrays, structures and unions and displaying long comments for variables (up to five lines) are supported by version 1.04 or higher.

³ Changing the length of the displayed variable comments is supported by version 1.05 or higher.

⁴ Creating programs in a library file is supported by version 1.06 or higher.

⁵ Supported only by the Sysmac Studio version 1.08 or higher.

⁶ The .csm format is supported by version 1.04 or higher. The size of a csm file is smaller than the size of the smc file.

⁷ Merging detailed comparison results is supported by version 1.03 or higher.

⁸ Changing present values in the ladder editor or ST editor is supported by version 1.03 or higher.

⁹ Changing the colors of graph lines is supported by version 1.01 or higher.

¹⁰ Consecutively reading and displaying continuous trace results from more than one file is supported by version 1.05 or higher.

¹¹ MATLAB®/Simulink R2013a or higher is required.

¹² CX-Designer version 3.41 or higher is required.

¹³ Individual selection of the retained variables to restore is supported by version 1.05 or higher.

DB connection functions

Item		Description
Setting parameters	DBMS settings	The database to connect is selected.
	Run mode setting of the DB connection service	The operation mode is selected to send SQL statements when DB connection instructions are executed or test mode is selected to not send SQL statements when DB connection instructions are executed.
	Spooling settings	You can set the service so that SQL statements are spooled when problems occur and resent when operation is restored.
	Operation log settings	Settings are made for the execution log for execution of the DB connection service, the debug log for execution of SQL statements for the DB connection service and the SQL execution failure log for SQL execution failures.
	Database connection service shutdown settings	Settings are made to control operation in order to end the DB connection service after automatically storing the operation log files on an SD memory card.
Programming	DB connection instructions	You can use the following DB connection instructions to write the user program for controlling the data in the database: DB_Insert (insert DB record), DB_Select (retrieve DB record), DB_Update (update DB record) and DB_Delete (delete DB record)
Monitoring information	Monitoring the DB connection service	The status of the DB connection service is monitored.
	Monitoring the DB connections	The status of each DB connection is monitored.
	Displaying the operation logs	The contents of the execution log, debug log and SQL execution failure log are displayed.

Note: The DB connection service can be used if the NJ501-1□20 is selected with Sysmac Studio version 1.06 or higher.

Safety control unit functions

Item		Description	
Setting parameters	Safety I/O settings	Safety I/O settings	You make a setting for safety process data communications and connection with safety I/O devices.
		Safety process data communications settings	You select safety I/O units to perform safety process data communications (FSOE communications) and make necessary settings.
		Safety device allocation settings	You set the connection between safety I/O units and safety devices.
	Standard I/O settings	Exposed variable settings	You set whether to expose global variables of the safety CPU unit. The values of exposed variables can be referenced from NJ-series CPU units.
		Standard process data communications ¹	You set the devices and ports of the standard I/O units for the exposed variables of the safety CPU unit.
	Safety task	Settings	You define the execution cycle and timing of the safety task and programs to be executed in the task.
		Assigning programs	You assign safety programs to execute the task.
I/O map settings		The ports of safety I/O units used in safety process data communications are displayed. You assign device variables used in safety programs to the I/O ports.	
Creating safety programs	Instruction list (Toolbox)		A hierarchy of the functions and function blocks that you can use is displayed in the toolbox. You can drag the required functions and function blocks onto the FBD editor to insert it to a safety program.
	FBD programming	FBD programming	You connect variables, functions and function blocks with connecting lines to build networks. The FBD editor is used to enter them.
		Adding FBD networks	You create FBD networks on the FBD editor to create algorithms.
		Inserting/Deleting functions/function blocks	You insert and delete functions and function blocks on the FBD editor.
		Entry assistance	When you enter functions, function blocks or parameters, each character that you enter from the keyboard narrows the list of candidates that is displayed for selection.
	Commenting out FBD networks		You can comment out each FBD network. When a network is commented out, it is no longer executed.
	Creating variables		You create variables used in safety programs in the global or local variable table.
	Function Blocks	Function Blocks	You create user-defined function blocks.
Help reference ²		You can display the user-defined function block help with the popup menu or shortcut key.	
Export/import ²		You can export/import user-defined function blocks.	
Searching and replacing		You can search for and replace strings in the variable tables, programs and function blocks of a safety CPU unit.	
Debugging	Monitoring		Variables are monitored during safety program execution. You can monitor the present values of device variables assigned to safety I/O units and user-defined variables. The values can be monitored on the FBD editor or watch tab page.
	Changing the present values of variables		You can change the present values of user-defined variables and device variables as required. You can do this on the FBD editor or watch tab page.
	Forced refreshing		The inputs from external devices and outputs to external devices are refreshed with a specified value on the Sysmac Studio. The specified value is retained even if the value of the variable is overwritten from the user program. You can use forced refreshing on the FBD editor or watch tab page.
	Offline debugging ³		You can check if the control program logic works as designed in advance using a special debugging function for the Simulator without connecting online with the safety CPU unit.
	User memory usage monitor ⁴		The memory usage of the safety control system and usage of safety network such as I/O data size are displayed.
Safety	Safety validation		You append the "safety-validated" information to a safety program when you can ensure safety of the program after you complete debugging.
	Changing operation mode		There are four operating modes: PROGRAM mode, DEBUG mode (STOPPED), DEBUG mode (RUN) and RUN mode. The RUN mode can be selected only for the validated safety programs.
Security measures	Setting the node name		You set a unique name for each safety CPU unit to confirm that you operate the correct safety CPU unit.
	Safety password		You can prevent unauthorized access to safety functions of safety CPU units by setting a safety password for online operations that affect the safety functions.
	Data protection ²		You can set passwords for individual user-defined function block to prohibit displaying, changing them.

¹ Supported if the EtherNet/IP coupler is selected with Sysmac Studio version 1.11 or higher.

² Supported only by the Sysmac Studio version 1.12 or higher.

³ Supported only by the Sysmac Studio version 1.08 or higher.

⁴ Supported only by the Sysmac Studio version 1.10 or higher.

Note: Supported only by Sysmac Studio version 1.07 or higher.

HMI functions

NA-series programmable terminals

Item		Description	
Parameter settings	Device	References	Devices, such as controllers, through which the NA-series PT can read and write information with communications are created on the Sysmac Studio and settings are made for them.
		Displaying internal devices	Controllers that were created in the project are displayed.
		Registering external devices	Devices, such as controllers, that were not created in the project are registered. The communications settings of the devices to communicate with the NA-series PT and information, such as variables and addresses within the devices that the NA-series PT will read and write, are also registered.
	Mapping variables		The information on the devices registered in the device references, such as variables and addresses, are mapped to the global variables of the NA-series PT.
	Settings	HMI	Settings for NA-series PT operation are made.
		Device	Settings, such as the startup page, default language, layout of the USB keyboard, automatic logout, screen saver, screen brightness and method to change to the system menu are made.
		TCP/IP	Settings for the Ethernet port, that is built-in to the NA-series PT, are made.
		FTP	Settings to communicate with FTP clients using the Ethernet port are made.
		NTP	Settings to communicate with an NTP server using the Ethernet port are made.
		FINS	Settings to communicate with devices that support FINS are made.
		VNC	Settings to communicate with VNC clients using the Ethernet port are made.
		Security	Settings, such as user registration and permissions to restrict NA-series PT operation and displays, are made.
		User account settings	The user names, login passwords and permissions for each user to operate the NA-series PT are set.
Permission and access level settings		The range of information that can be accessed for different permissions are set.	
Language	Language settings to perform multi-language displays on the NA-series PT are made.		
Creating data and programming	Pages	Editing pages	The pages to display on the NA-series PT are edited.
		Adding and deleting pages	Pages are added, deleted or copied with the Multiview Explorer. Pages can also be copied to other projects.
		Adding and deleting page groups	Groups to organize and manage pages on the Multiview Explorer are added and deleted. Pages can be added to or moved to the groups.
		Page properties settings	The page type, overlapping, background color, etc., are set in the Properties Window.
		Changing the display language	If using multiple languages is set in the language settings, the resources displayed on the Page Editor are displayed in the language set for each resource.
		Displaying object configuration	The objects and groups that were added to each page can be confirmed in a tree structure using the Page Explorer.
		Adding objects	Objects, such as buttons or graphics, to display on a page are added by dragging them from the Toolbox to the Page Editor.
		Grouping objects	Settings to operate multiple objects together as a group are made.
		Aligning objects	Multiple objects are aligned.
		Editing objects	Objects and groups can be copied within a page or to another page. Objects can also be deleted and locations, sizes, rotations and position relationships with other objects can be set.
		Object property settings	Properties, such as the colors and shapes of objects and the mapped variables, can be changed. Properties are displayed and changed in the Properties Window.
		Animation settings	Animation to modify dynamically the appearance of objects are set. Animation is displayed and changed in the Animation Window.
		Event and action settings	The events that can be set for objects and the actions that can be executed when an event occurs are set.
	Programming with Visual Basic	Visual Basic	Subroutines are created with Visual Basic.
		Language specifications	Visual Basic 2008 and .NET Compact Framework 3.5 are supported. ¹
		Adding subroutine groups	Groups to organize and manage global subroutines on the Multiview Explorer are added or deleted. Subroutines can be added or moved to the groups.
		Editing subroutines	Subroutines are created using the Code Editor, which is optimized for Visual Basic.
		Bookmarks	Bookmark can be added to any code line and you can move between the bookmarks.
		Data entry assistance	The characters that are entered from the keyboard are used to display candidates when entering the source code.
	User alarms	User alarms	Settings for detection conditions and displaying messages for user alarms are made.
		Adding and deleting user alarm groups	Groups to organize and manage user alarms on the Multiview Explorer are added or deleted. User alarms can be created in the groups.
		Registering and deleting user alarm	Setting for detection conditions for user alarms and displaying messages or popup pages are made for user alarm groups.
		Copying user alarms	User alarms can be copied within a group or to another group.
		Event and action settings	Events and the actions that are executed when the events occur are set for the user alarms. Displaying and changing the settings for events and actions is performed in the Events and Actions Window.
	Data logging	Data logging	Data logging is set to log specified data in the NA-series PT at the specified times.
		Adding and deleting data sets	Data sets are added to perform data logging.
		Log condition setting	Conditions to perform data logging and target global variables are set for the data sets.
	Recipes	Recipes	Data groups that are retained in the NA-series PT and can be switched for user requests are set.
		Adding and deleting templates	Data storage locations, value ranges and data names are added or deleted.
		Recipe data settings	The actual data is set for each recipe.
	Global events		The events that are detected on any page and the actions that are executed when the events occur are set.

Item		Description	
Creating data and programming	Resource management	Management	All of the character strings and graphics that are displayed on pages are managed.
		Registering and deleting general character strings	The character strings that are displayed on pages are registered and deleted, except for character strings used for user alarms.
		Registering and deleting character strings for user alarms	The character strings used for user alarms are added or deleted.
		Registering and deleting document files	Document files that are displayed with the Document Viewer are set or deleted.
		Registering and deleting image files	Image files that are displayed for objects are set or deleted.
		Registering and deleting movies	Movie files that are displayed for Media Player objects are set or deleted.
		Importing and exporting	The general character strings and alarm character strings can be imported and exported using Excel files.
	Searching and replacing	You can search for and replace character strings in subroutines that are created with Visual Basic.	
	Building	The project is converted into a format that can be executed in the NA-series PT.	
Reusability	IAGs	Intelligent application gadgets	Multiple objects and subroutines are combined to create a reusable object.
		Creating IAGs	An IAG is created as a functional unit in an IAG project.
		Creating IAG collection files	A created IAG is built and saved as a module that can be distributed and reused.
		Using IAGs	IAG collection files are imported using the IAG Collection Manager. The imported IAGs are displayed in the Toolbox and can be used in the same way as other objects.
	Custom objects	Custom objects	The selected objects are registered in a reusable format in the Toolbox.
Registering custom objects		Objects or grouped objects are dragged to the Toolbox to register them.	
Using custom objects		Custom objects are displayed on a page by dragging them from the Toolbox to the Page Editor.	
File operations	Synchronization		The data in the NA-series PT that is online is compared with the data in the Sysmac Studio. You can check the differences and then transfer the data after specifying the transfer direction.
	Transferring files via storage media		The data in a storage media in the computer is compared with the data in the Sysmac Studio. You can check the differences and then transfer the data to the storage media. You can use the System Menu to transfer a saved project file to the NA-series PT.
	Clearing all memory		All of the data except for the clock information is deleted from the NA-series PT.
Simulation	Executing simulations		A project file on the computer is virtually executed to debug it.
	Setting and clearing breakpoints		Breakpoints can be set at the specified positions in a subroutine.
	Synchronized simulation with Controller Simulator		Sequence control and NA-series PT operation, such as displaying pages and subroutine operation, is simulated together to debug the application in the NA-series PT.
	Setting clock information		The clock information in the NA-series PT can be checked and set.
Communications	Going online with NA-series PT		The computer can be placed online with the NA-series PT. However, information in the NA-series PT, such as the values of variables, cannot be read.
	Upgrading system program		When the Sysmac Studio is online with the NA-series PT, the system program in the NA-series PT can be upgraded as required.
Security	Preventing malfunctions		If the name or serial ID of the project and the NA-series PT are different when the Sysmac Studio goes online, a confirmation dialog box is displayed.
	Preventing incorrect operations		You can prevent data in the NA-series PT from being overwritten from the Sysmac Studio.

¹ There are restrictions on the functions that can be used.

Note: Supported only by Sysmac Studio version 1.11 or higher.

Vision sensor functions

FQ-M vision sensor

Item		Description	
Setting parameters	Main edit	General settings	Displays and sets basic information of the sensor.
		Sensor connection	Changes the connection status of the sensor, and sets the conditions for communications with the sensor.
		Sensor control in online	Performs various controls for the sensor mode change, data transfer/save and monitoring.
		Sensor error history	Displays and clears the error history of an online sensor.
		Tool	Restarts and initializes the sensor, updates the firmware of the sensor, reads sensor data from a file, saves a sensor data to a file, prints the sensor parameters and displays help.
	Scene data edit	Image condition settings	Adjusts the image condition.
		Specifies the calibration pattern	Sets a registered calibration pattern.
		Registers inspection item	Registers the inspection item to use in the measurement. You can select from the following inspection items: edge position, search, labeling, shape search.
		Calculation settings	Makes a setting for basic arithmetic operations and function operations using inspection item judgment results and measurement data.
		Logging settings	Makes a setting for logging measurement results of inspection items and calculation results.
		Output settings	Makes a setting for data to output to external devices.
		Run settings	Switch sensor modes or monitors measurement results.
	Sensor system data edit	Trigger condition settings	Sets the trigger type and image timing.
		I/O settings	Sets the conditions of output signals. You can check the status of I/O signal while online.
		Encoder settings	Make settings for the encoder such as common encoder settings, ring counter settings and encoder trigger settings.
		Ethernet communication settings	Makes Ethernet communication settings. You can select data communication from no-protocol data, PLC link data and programmable no-protocol data.
		EtherCAT communication settings	Makes the EtherCAT communication settings according to the communication settings of the EtherCAT master.
		Logging condition settings	Sets the conditions to log to the internal memory of sensor.
		Sensor settings	Makes the settings for startup scene control function, password setting function and adjustment judgment function.
	Calibration scene data settings		Calculates, views and edits the calibration parameters. The vision sensor supports general-purpose calibration and calibration for conveyor tracking.
Debugging	Offline debugging of sensor operation		Simulates measurements offline without connecting to the vision sensor. You can use external image files and perform measurements under the conditions set in the offline settings, then display the results of those measurements.
	Offline debugging of the sensor control program and sensor operation		Performs a linked simulation between the sequence control of an NJ-series controller and the operation of an FQ-M sensor in EtherCAT configuration systems. This allows you to debug operation offline from when measurements and other processing are performed for control signals such as measurement triggers through the output of processing results.

Note: Supported only by the Sysmac Studio version 1.01 or higher.

FH vision sensor

Item		Description	
Setting parameters	Main edit	Sensor information	Displays and sets basic information of the sensor.
		Online	Changes the connection status of the sensor and performs various controls such as sensor restart and initialization.
	Line edit	Operation view	Monitors the measurement images of the sensor and detailed results of each process unit.
		Scene maintenance view	Edits, manages and saves the scene groups and scenes.
	Scene data edit	Flow edit	Creates the process flow in combination of user-specified units.
		Process unit edit	Edits each process unit.
	Sensor system data edit	Camera settings	Checks the camera connection status and sets the camera's imaging timing and communications speed.
		Controller settings	Makes the system environment settings for the sensor.
		Parallel I/O settings	Sets the conditions of output signals.
		RS-232C/422 settings	Makes the RS232C/422 communications settings.
		Ethernet communication settings	Makes the Ethernet communication settings.
		EtherNet/IP communication settings	Makes the EtherNet/IP communication settings.
		EtherCAT communication settings	Makes the EtherCAT communication settings.
		Encoder settings	Makes the encoder settings.
	Tools	Communication command customization tool	Makes the settings for customized communication commands.
		File saving tool	Copies and transfers the files in the sensor memory.
		Calibration support tool	Checks the calibration information.
		User data tool	Edits the data (user data) that can be shared and used in sensors.
		Security setting tool¹	Edits the security settings of the sensor.
		Scene group save destination setting tool¹	Sets the destination to save the scene group data.
		Image file save tool¹	Saves the logging images and image files stored in the sensor memory.
		Registered image management tool¹	Saves the images used for model registration and reference registration as registered images.
		Reference position update tool¹	Edits all reference positions of more than one processing unit.
		Scene group data conversion tool¹	Creates the scene group data with more than 128 scenes.
		Scene control macro tool¹	Makes a setting for complementing and expanding the measurement flow and scene control.

Item		Description
Debugging	Offline debugging of sensor operation	Simulates measurements offline without connecting the sensor. You can use external image files and perform measurements under the conditions set in the offline settings, then display the results of those measurements.
	Offline debugging of sensor control program and sensor operation ²	Simulates the linked operation of the sequence controls in the NJ-series controller and FH-series sensor operation for an EtherCAT system. You can debug a series of operations offline to perform the measurement and other processing and output the results when a control signal such as measurement trigger is input to the sensor.
Security	Prevention of incorrect operation ³	Prevents unauthorized access by setting an account password for online operations.

¹ Supported only by the Sysmac Studio version 1.10 or higher.

² Supported only by the Sysmac Studio version 1.08 or higher.

³ Supported only by the Sysmac Studio version 1.09 or higher.

Note: Supported only by the Sysmac Studio version 1.07 or higher.

Displacement sensor functions

Item		Description	
Setting parameters	Main editing	General settings	Displays and sets basic information on the sensor.
		Sensor connection	Changes the connection status of the sensor, and sets the conditions for communications with the sensor.
		Online sensor control	Performs various controls for the sensor (e.g., changing the mode, controlling internal logging and monitoring).
		Tools	Restarts and initializes the sensor, updates the firmware in the sensor, recovers ROM data, prints the sensor parameters and displays help.
	Editing bank data	Setting sensing conditions	Adjusts the light reception conditions for each measurement region.
		Setting task conditions	Used to select the measurement items to use in measurements. You can select from the height, thickness or calculations. The following are set for the measurement items: scaling, filters, holding, zero-resetting and judgement conditions.
		Setting I/O conditions	Sets parameters for outputting judgements and analog values to external devices.
		Sensor settings	Sets the following: ZW sensor controller's key lock, number of displayed digits below the decimal point, the bank mode, the analog output mode and timing/reset key inputs.
		Ethernet communication settings	Sets up Ethernet communications and field bus parameters.
		RS-232C communication settings	Sets up RS-232C communications.
	Data output settings	Sets serial output parameters for holding values.	
Debugging	Offline debugging of sensor control programs and sensor operation	Performs a linked simulation between the sequence control of an NJ-series controller and the operation of a ZW sensor in EtherCAT configuration systems. This allows you to simulate the operation of signals when timing signals and other control signals are input to the sensor to debug the control logic offline.	

Note: Supported only by the Sysmac Studio version 1.05 or higher.

EtherNet/IP connection functions

Item		Description	
EtherNet/IP connection settings	Connection settings		Functions related to tag data links (connection) settings in the EtherNet/IP network are provided.
	Setting connections	Editing tag sets	You create tags and tag sets using network variables.
		Editing target devices	You add target devices to connect to.
		Editing connections	You select tag sets from a list and create connections.
		Adding EDS files	You can add the types of EtherNet/IP devices that can be set as targets.
	Transferring connections	Synchronized transfer and batch transfer	All the connection settings in the controller or the project are transferred at the same time.
		Individual transfer and comparison	You can transfer or compare the connection settings of each EtherNet/IP device individually.
	Monitoring connections	Status monitor	The operating status of one or more connections is displayed. You can start or stop all the connections at the same time.
		Tag/tag set monitor	The detailed operation information of tags and tag sets, such as the presence or absence of tags and connection times of tag sets, is displayed.
		Ethernet information monitor	The detailed operation information of EtherNet/IP devices, such as bandwidth usage (pps), is displayed.

Note: Supported only by the Sysmac Studio version 1.10 or higher.

EtherNet/IP slave terminal functions

Item		Description
EtherNet/IP slave terminal configuration and setup	Configuration and setup	You create the configuration of slave terminal to be connected to the EtherNet/IP network on the Sysmac Studio and set the NX units that compose the slave terminal.
	Registering the NX units	You configure the slave terminal by dragging the NX units from the device list displayed in the toolbox to the positions where to mount the units.
	Setting the NX units	You edit the I/O allocation settings, mounting settings and unit operation settings of the NX units.
	Displaying the width of slave terminal configuration	The width and power consumption of the slave terminal configuration are displayed based on the unit configuration information.
	Comparing and merging the slave terminal configuration information	You can compare the configuration information on the project with actual configuration online, select the units with different information to correct and merge the information.
	Transferring the slave terminal configuration information	You transfer the unit configuration information to the slave terminal.

Note: Supported only by the Sysmac Studio version 1.11 or higher.

Web support services

Category	Function
Online user registration	You can register online as a user of Sysmac Studio.
Automatic update	With the automatic update function of Sysmac Studio, the latest update information for your computer environment can be searched for and applied using the Internet. Your Sysmac Studio can be constantly updated to the latest state.

Ordering information

Automation software

Please purchase a DVD and licenses the first time you purchase the Sysmac Studio. DVD's and licenses are available individually. The license does not include the DVD.

Product	Specifications			Model
	Description	Number of licenses	Media	
Sysmac Studio Standard Edition Ver. 1.□□	The Sysmac Studio is the software that provides an integrated environment for setting, programming, debugging and maintenance of machine automation controllers including the NJ-series, EtherCAT slave and the HMI. Sysmac Studio runs on the following OS: Windows XP (Service Pack 3 or higher, 32-bit version) Windows Vista (32-bit version) Windows 7 (32-bit/64-bit version) Windows 8 (32-bit/64-bit version) Windows 8.1 (32-bit/64-bit version)	– (Media only)	DVD ^{*1}	SYSMAC-SE200D
		1 license	–	SYSMAC-SE201L
		3 licenses	–	SYSMAC-SE203L
		10 licenses	–	SYSMAC-SE210L
		30 licenses	–	SYSMAC-SE230L
		50 licenses	–	SYSMAC-SE250L
Sysmac Studio Vision Edition Ver. 1.□□ ^{2,4}	Sysmac Studio Vision Edition is a limited license that provides selected functions required for FQ-M series and FH-series vision sensor settings.	1 license	–	SYSMAC-VE001L
Sysmac Studio Measurement Sensor Edition Ver. 1.□□ ^{3,4}	Sysmac Studio Measurement Sensor Edition is a limited license that provides selected functions required for ZW-series displacement sensor settings.	1 license	–	SYSMAC-ME001L
		3 licenses	–	SYSMAC-ME003L
Sysmac Studio NX-I/O Edition Ver. 1.□□ ^{4,5}	Sysmac Studio NX-I/O Edition is a limited license that provides selected functions required for EtherNet/IP coupler settings.	1 license	–	SYSMAC-NE001L

^{*1} The same media is used for both the Standard Edition and the Vision Edition.
^{*2} With the Vision Edition, you can use only the setup functions for FQ-M series and FH-series vision sensors.
^{*3} With the Measurement Sensor Edition, you can use only the setup functions for ZW-series displacement sensors.
^{*4} This product is a license only. You need the Sysmac Studio Standard Edition DVD media to install it.
^{*5} With the NX-I/O Edition, you can use only the setup functions for EtherNet/IP coupler.

Note: Site licenses are available for users who will run Sysmac Studio on multiple computers. Ask your OMRON sales representative for details.

Components

DVD (SYSMAC-SE200D)

Components	Details
Introduction	An introduction about components, installation/uninstallation, user registration and auto update of the Sysmac Studio is provided.
Setup disk (DVD-ROM)	1

License (SYSMAC-SE2□□L/VE0□□L/ME0□□L/NE0□□L)

Components	Details
License agreement	The license agreement gives the usage conditions and warranty for the Sysmac Studio.
License card	A model number, version, license number and number of licenses are described.
User registration card	Two cards are contained. One is for users in Japan and the other is for users in other countries.

Included support software

DVD media of Sysmac Studio includes the following support software:

Included support software	Outline
CX-Designer Ver. 3.□□	The CX-Designer is used to create screens for NS-series PTs.
CX-Integrator Ver. 2.□□	The CX-Integrator is used to set up FA networks.
CX-Protocol Ver. 1.□□	The CX-Protocol is used for protocol macros for serial communications units.
Network Configurator Ver. 3.□□	The Network Configurator is used for tag data links on the built-in EtherNet/IP port.
SECS/GEM Configurator ^{*1} Ver. 1.□□	The SECS/GEM Configurator is used for SECS/GEM settings.

^{*1} Please, purchase the required number of SECS/GEM Configurator licenses.

ALL DIMENSIONS SHOWN ARE IN MILLIMETERS.
 To convert millimeters into inches, multiply by 0.03937. To convert grams into ounces, multiply by 0.03527.